



Digital HDTV Over-the-Air Antenna w/built-in Digital TV Signal Meter

OA8200 – White
OA8201 – Black

Specifications



Dimensions: 11.25”H x 16”W x 12.5”L

Weight: 2.3 lbs.

Frequency Bands: VHF (47-230Mhz) – 20 dB gain

UHF (470-860 Mhz) – 25 dB gain

Powered Amplifier: +12 volt / 100 mA working

Power supplied via wall mount power switch
Mfr. # 21015 – White with inputs for Antenna
and Cable and 2 TV outputs.

Signal Meter

Frequency Response: 40-862 Mhz (Ch 2-69)



Enclosure/Mount: ASA – Automotive grade

Wider reception range

Less directional than traditional RV antennas to provide broader reception coverage.

Greatly improved UHF reception

Superior reception of UHF signals where over 80% of new DTV channels are broadcast, also offers great reception of remaining VHF channels.

Built-in Amplifier

Enhance weak signals in fringe areas for improved reception. Flush wall mount power switch with cable/antenna inputs and 2 TV outputs available in white or black.

Compact, aerodynamic design

Aerodynamic mount offers superior wind resistance, is 70% smaller and requires less roof space than traditional RV antennas.

Built-in Digital TV Signal Meter

Point the antenna for maximum reception before scanning for channels to simplify set-up and eliminate frustration.

No crank handle

Fixed height requires no cranking up or down. No need to remember to stow antenna before driving away.

Effortless antenna rotation

Easily rotate antenna with two fingers.

Easy to install

Works with varying roof thickness and easily replaces existing antenna.

Full 360° Rotation

No reception dead-spot due to rotational limit commonly found with other antennas.



Phone: (952) 922-6889

Website: www.kingcontrols.com